

Surge arrester

2-electrode arrester

Series/Type: EC150X Ordering code: B88069X

Ordering code: B88069X0880S102

Version/Date: Issue 05 / 2007-04-19



Surge arrester B88069X0880S102

2-electrode arrester **EC150X**

Features	Applications	
 Standard size 	■ Modem	
 High current rating 	 XDSL-splitter 	
 Very fast response time 	Data lines	
 Stable performance over life 	■ Tuner	
 Very low capacitance 	Antenna	
 High insulation resistance 		
 RoHS-compatible 		

Electrical specifications

DC spark-over voltage 1) 2)	150	V
Do spark ever verlage	± 20	%
Impulse spark-over voltage		
at 100 V/µs - for 99% of measured values	< 500	V
- typical values of distribution	< 450	V
at 1 kV/µs - for 99% of measured values	< 650	V
- typical values of distribution	< 550	V
Service life		
10 operations 50 Hz, 1 s	5	Α
1 operation 50 Hz, 0.18 s (9 cycles)	20	Α
10 operations 8/20 μs	5	kA
1 operation 8/20 μs	10	kA
1 operation 10/350 μs	1	kA
Insulation resistance at 50 V _{DC}	> 10	$G\Omega$
Capacitance at 1 MHz	< 1 pF	
Arc voltage at 1 A	~ 12	V
Glow to arc transition current	~ 0.8	Α
Glow voltage	~ 80	V
Weight	~ 1.5	g
Operation and storage temperature	-40 +90	°C
Climatic category (IEC 60068-1)	40/ 90/ 21	
Marking, red positive	EPCOS EC 150 YY O	
	EC - Series	
	150 - Nominal voltage YY - Year of production	
	O - Non radioactive	

 $^{^{1)}}_{\rm 2)}$ At delivery AQL 0.65 level II, DIN ISO 2859 In ionized mode

Terms in accordance with ITU-T Rec. K.12 and DIN 57845/VDE0845


KB AB E / KB AB PM Issue 05 / 2007-04-19



Surge arrester B88069X0880S102

2-electrode arrester EC150X

Dimensional drawing



Cautions and warnings

- Surge arresters must not be operated directly in power supply networks.
- Surge arresters may become hot in the event of longer periods of current stress (danger of burning).
- Surge arresters may be used only within their specified values. In the event of overload, the lead contacts may fail or the component may be destroyed.
- Damaged surge arresters must not be re-used.



Important notes

The following applies to all products named in this publication:

- 1. Some parts of this publication contain statements about the suitability of our products for certain areas of application. These statements are based on our knowledge of typical requirements that are often placed on our products in the areas of application concerned. We nevertheless expressly point out that such statements cannot be regarded as binding statements about the suitability of our products for a particular customer application. As a rule, EPCOS is either unfamiliar with individual customer applications or less familiar with them than the customers themselves. For these reasons, it is always ultimately incumbent on the customer to check and decide whether an EPCOS product with the properties described in the product specification is suitable for use in a particular customer application.
- 2. We also point out that in individual cases, a malfunction of passive electronic components or failure before the end of their usual service life cannot be completely ruled out in the current state of the art, even if they are operated as specified. In customer applications requiring a very high level of operational safety and especially in customer applications in which the malfunction or failure of a passive electronic component could endanger human life or health (e.g. in accident prevention or life-saving systems), it must therefore be ensured by means of suitable design of the customer application or other action taken by the customer (e.g. installation of protective circuitry or redundancy) that no injury or damage is sustained by third parties in the event of malfunction or failure of a passive electronic component.
- 3. The warnings, cautions and product-specific notes must be observed.
- 4. In order to satisfy certain technical requirements, some of the products described in this publication may contain substances subject to restrictions in certain jurisdictions (e.g. because they are classed as "hazardous"). Useful information on this will be found in our Material Data Sheets on the Internet (www.epcos.com/material). Should you have any more detailed questions, please contact our sales offices.
- 5. We constantly strive to improve our products. Consequently, **the products described in this publication may change from time to time**. The same is true of the corresponding product specifications. Please check therefore to what extent product descriptions and specifications contained in this publication are still applicable before or when you place an order.
 - We also **reserve the right to discontinue production and delivery of products**. Consequently, we cannot guarantee that all products named in this publication will always be available.
- 6. Unless otherwise agreed in individual contracts, all orders are subject to the current version of the "General Terms of Delivery for Products and Services in the Electrical Industry" published by the German Electrical and Electronics Industry Association (ZVEI).
- 7. The trade names EPCOS, EPCOS-JONES, Alu-X, Baoke, CeraDiode, CSSP, MLSC, PhaseCap, PhaseMod, SIFERRIT, SIFI, SIKOREL, SilverCap, SIMID, SIOV, SIP5D, SIP5K, UltraCap, WindCap are **trademarks registered or pending** in Europe and in other countries. Further information will be found on the Internet at www.epcos.com/trademarks.